

Parc de Belloch  
Ctra. C-251 Km 5,6  
E-08430 La Roca, Barcelona  
España / Spain  
tel. +34 938 462 437  
fax +34 938 711 767  
www.santacole.com

## Candela LED

February 2013

### 3000K – IRC85 (typical)

Nº LEDS	Ref. Luminaire	LED current [mA]	Nominal lamp power [W]	System power [W]	Luminaire output luminous flux [lm]
48	CLF48A1	350	50	54	4.000
	CLF48B1	500	70	78	5.000
72	CLF72A1	350	75	82	6.000
	CLF72B1	500	105	117	7.400
88	CLF88A1	350	90	100	7.300
	CLF88B1	500	130	143	9.100
96	CLF96A1	350	100	108	8.000
	CLF96B1	500	140	156	10.000

### 4000K – IRC75 (typical)

Nº LEDS	Ref. Luminaire	LED current [mA]	Nominal lamp power [W]	System power [W]	Luminaire output luminous flux [lm]
48	CLF48A2	350	50	54	5.000
	CLF48B2	500	70	78	6.200
72	CLF72A2	350	75	82	7.500
	CLF72B2	500	105	117	9.300
88	CLF88A2	350	90	100	9.200
	CLF88B2	500	130	143	11.400
96	CLF96A2	350	100	108	10.000
	CLF96B2	500	140	156	12.400